
AC28G-04




DISASSEMBLY

1. REMOVE PRESSURE PLATE

(a) Using SST and a socket wrench, remove the shaft bolt. SST 07112-76050


Torque: 13.2 N·m (135 kgf·cm, 9 ft·lbf)



- (b) Install SST to the pressure plate. SST 07112-66040
- (c) Using SST and a socket wrench, remove the pressure plate.


SST 07112-76050, 07112-66040

(d) Remove the shims from the shaft.



2. REMOVE ROTOR


(a) Using SST, remove the snap ring. SST 95994-10020



NOTICE:

At the time of reassembly, please refer to the following item.

The snap ring should be installed so that its beveled side faces up.




(b) Using a plastic hammer, tap the rotor off the shaft.

NOTICE:

Be careful not to damage the pulley when tapping on the rotor.


2002 ECHO (RM884U)

Author: Date: 1492




3. REMOVE STATOR

- (a) Disconnect the connector from the stator.
- (b) Remove the screw and stator lead wire.




(c) Using SST, remove the snap ring. SST 95994-10020



NOTICE:

At the time of reassembly, please refer to the following item.

The snap ring should be installed so that its beveled side faces up.



(d) Remove the stator.

2002 ECHO (RM884U)

Author: Date: 1493